

ISO 9001 REGISTERED

Powertech Labs Inc. 12388 - 88th Avenue

Surrey, British Columbia Canada V3W 7R7

Tel: (604)590-7500 Fax: (604)590-5347

www.powertech.bc.ca

CONTROLLER SIMULATED SURGE ARRESTER OPERATION TEST REPORT

Client:	Schweitzer Engineering Laboratories, 2350 NE Hopkins Court, Pullman, WA 99163-5603, USA				
Test Date:	16 & 17 May 2006		Project:	16533-27	
Nameplate Data Controller: Manufacturer: Model: Part No.: Serial No.: Recloser: Manufacturer: Type: Impulse level (BI Rated voltage: Rated current: Serial No.:	Schweitzer E SEL-651R 0651R0618A 2006088298 Cooper Powe NOVA-TS-15 110 kV _{peak} 15.5 kV _{rms}	8203X1XX er Systems, Milwau inuous; 8 kA interr	ukee WI USA	Washington, USA	
Test Witness:	Darin McKee	, Schweitzer Engir	neering Laborat	ories	
Test Standard:	IEEE Std C3	7.60-2003, Clause	6.13.2: "Simula	ted Surge Arrester Operation Test"	
Atmospheric Co	Rela	nperature ative humidity ometric pressure	24.1 °C 38% 758.4 mm	Hg	
Test Current:	7 kA _{peak}				
Test Configurations (in accordance with the above standard):					
	B – surges a C – surges a D – surges a E – surges a If the device omitted. Th	A – surges applied to the source bushing with the recloser open B – surges applied to the source bushing with the recloser closed C – surges applied to the load bushing with the recloser closed D – surges applied to a properly rated transformer with the recloser open E – surges applied to a properly rated transformer with the recloser closed If the device under test has a self-contained power source, conditions D and E may be omitted. This controller is designed to be powered by isolated dc batteries, so configuration D and E were omitted.			
Test Results:			BS	v following the Simulated Surge Arrester	
	Operation Te standard. T	The controller and recloser operated normally following the Simulated Surge Arrester Operation Test performed in accordance with the test procedures as per the above standard. The controller complied with the requirements of IEEE Std C37.60-2003, Clause 6.13.2.			
Remarks:	None				

Prepared by:

Approved by:

May Wang, P.Eng. Senior Electrical Engineer

A.J. Vandermaar, P.Eng. 26 1 Manager, High Voltage Laboratory



ISO 9001 REGISTERED

Powertech Labs Inc. 12388 - 88th Avenue Surrey, British Columbia

Canada V3W 7R7

Tel: (604)590-7500 Fax: (604)590-5347 www.powertech.bc.ca

CONTROLLER OSCILLATORY SWC TEST REPORT

Client:	Schweitzer Engineering Laboratories, 2350 NE Hopkins Court, Pullman, WA 99163-5603, USA		
Test Date:	May 16, 2006	Project: 16533-27	
Nameplate Data Controller: Manufacturer: Model: Part No.:	Manufacturer: Schweitzer Engineering Laboratories, Pullman, Washington, USA Model: SEL-651R		
Serial No.:	2006088298	· ·	
Recloser: Manufacturer: Type: Impulse level (BI Rated voltage: Rated current: Serial No.:	Cooper Power Systems, M NOVA-TS-15 110 kV _{peak} 15.5 kV _{rms} 400 A _{rms} continuous; 8 kA 000101, 000125, 000127		
Test Witness:	Darin McKee, Schweitzer	Engineering Laboratories	
Test Standard:	IEEE Std C37.60-2003, Cl	ause 6.13.1: "Oscillatory and fast transients surge tests"	
Test Voltage:	2.5 kV _{peak}		
Test Procedure:	Test surge applied in comr	mon mode and transverse mode to wire pairs.	
Test Results: The controller and recloser operated normally following the Oscillatory SW performed in accordance with the test procedures. The controller complication requirements of IEEE C37.60-2003, Clause 6.13.1.			
Remarks:	The controller passed the test.		

Tested by:

Approved by:

Robert G. Pollock

Senior Project Specialist

blor May 30/06

A. John Vandermaar, P.Eng.

Manager, High Voltage Laboratory

Oscillatory SWC Waveform Validity Tests

(in accordance with IEEE Std C37.90.1-2002, Clause A.2)

Performed before the Oscillatory SWC Test

Measuring system feedthrough test

Generator Output voltage _____ 2.5 ___ kV

Feedthrough voltage _____3 V (pass ≤ 1%)

Open circuit voltage waveform test

Recorded waveforms - Figures 1 and 2.

Test Generator performance verification 3.

Rise time of the first peak

72 ___ ns (60 to 90 ns - 10% to 90%)

Peak voltage level (no load)

2.5 kV

(2.25 to 2.5 kV when set to 2.5 kV)

Output impedance

191 Ω

 $(160 \text{ to } 240 \Omega)$

Waveform envelope decay

4.92 __ μs

(4 to 6 µs to 50%)

Oscillation frequency

0.91 MHz (0.9 to 1.1 MHz)

Repetition rate

8 bursts per period (6-10 bursts per 16.7 mS)

Test duration

2.1 s

(2 to 2.2 s)

Test Pass X Test Fail




Figure 1




Figure 2

Oscillatory SWC Waveform Validity Tests

(in accordance with IEEE Std C37.90.1-2002, Clause A.2)

Performed after the Oscillatory SWC Test

4. Measuring system feedthrough test

Generator Output voltage _____ kV

Feedthrough voltage 4.1 V (pass ≤ 1%)

Open circuit voltage waveform test

Recorded waveforms - Figures 1 and 2.

Test Generator performance verification

Rise time of the first peak

86 ns (60 to 90 ns - 10% to 90%)

Peak voltage level (no load)

2.3 kV (2.25 to 2.5 kV when set to 2.5 kV)

Output impedance

232 Ω

 $(160 \text{ to } 240 \Omega)$

Waveform envelope decay

4.4 _ µs

(4 to 6 µs to 50%)

Oscillation frequency

0.93 MHz

(0.9 to 1.1 MHz)

Repetition rate

8 bursts per period (6-10 bursts per 16.7 mS)

Test duration

2.17 s

(2 to 2.2 s)

Test Pass X Test Fail




Figure 1




Figure 2



ISO 9001 REGISTERED

Powertech Labs Inc. 12388 - 88th Avenue

Surrey, British Columbia Canada V3W 7R7 Tel: (604)590-7500 Fax: (604)590-5347 www.powertech.bc.ca

CONTROLLER FAST TRANSIENT SWC TEST REPORT

Client:	Schweitzer Engineering Laboratories, 2350 NE Hopkins Court, Pullman, WA 99163-5603, USA			
Test Date:	May 15, 2006	Project: 16533-27		
Nameplate Data: Controller: Manufacturer: Schweitzer Engineering Laboratories, Pullman, Washington, USA SEL-651R Part No.: O651R0618A8203X1XX Serial No.: 2006088298 Recloser: Manufacturer: Cooper Power Systems, Milwaukee WI USA Type: NOVA-TS-15 Impulse level (BIL): 110 kV _{peak} 15.5 kV _{rms} Rated current: 400 A _{rms} continuous; 8 kA interrupting Serial No.: 000101, 000125, 000127		203X1XX ystems, Milwaukee WI USA bus; 8 kA interrupting		
Test Witness:	Darin McKee, Sc	hweitzer Engineering Laboratories		
Test Standard:	IEEE Std C37.60	-2003, Clause 6.13.1: "Oscillatory and fast transients surge tests"		
Test Voltage:	4.0 kV _{peak}			
Test Procedure:	Test surge applie	ed in common mode and transverse mode to wire pairs.		
Test Results:	performed in acc	The controller and recloser operated normally following the Fast Transient SWC Test performed in accordance with the test procedures. The controller complied with the requirements of IEEE C37.60-2003, Clause 6.13.1.		
Remarks:	emarks: The controller passed the test.			

Tested by:

Robert G. Pollock

Senior Project Specialist

Melle May 30/06

Approved by:

A. John Vandermaar, P.Eng. Manager, High Voltage Laboratory

This report shall not be reproduced except in full, without the written approval of Powertech Labs Inc.

30 May 106

Fast Transient SWC Waveform Validity Tests (in accordance with IEEE Std C37.90.1-2002, Clause A.2)

Performed before the Fast Transient SWC Test

1. Measuring system feedthrough test

Generator Output voltage ____ kV

Feedthrough voltage _____ V (pass if \leq 1%)

2. Open circuit voltage waveform test

Recorded waveforms - Figures 1 and 2.

3. Test Generator performance verification

Rise time

3.85 ns

(3.5 to 6.5 ns - 10% to 90%)

Peak voltage level (no load)

4.0 kV

(3.6 to 4.4 kV when set to 4 kV)

Output impedance

47.9 Ω

 $(40 \text{ to } 60 \Omega)$

Impulse duration

60.2 ns

(35 to 65 ns to 50% value)

Repetition rate

2.5 kHz

(2 to 3 kHz)

Burst duration

<u>15.0</u> ms

(12 to 18 ms)

Burst period

300 ms

(240 to360 ms)

Test duration

_____s

 $(\ge 60 \text{ s})$

4. Test Pass X Test Fail




Figure 1




Figure 2

Fast Transient SWC Waveform Validity Tests (in accordance with IEEE Std C37.90.1-2002, Clause A.2)

Performed after the Fast Transient SWC Test

5. Measuring system feedthrough test

Generator Output voltage _____ kV

Feedthrough voltage $\underline{}$ V (pass if \leq 1%)

6. Open circuit voltage waveform test

Recorded waveforms - Figures 1 and 2.

7. Test Generator performance verification

Rise time

3.5 ns

(3.5 to 6.5 ns - 10% to 90%)

Peak voltage level (no load)

4.2 kV

(3.6 to 4.4 kV when set to 4 kV)

Output impedance

49.8 Ω

 $(40 \text{ to } 60 \Omega)$

Impulse duration

63 ns 2.5 kHz (35 to 65 ns to 50% value)

Repetition rate Burst duration 2.5 kHz 15.0 ms (2 to 3 kHz) (12 to 18 ms)

Burst period

300 ms

(240 to 360 ms)

Test duration

60.4 s

(≥ 60 s)

8. Test Pass X Test Fail




Figure 1




Figure 2