# SEL-2245-4 AC Metering Module

The SEL-2245-4 provides ac metering inputs for the SEL Axion<sup>®</sup>. Within an Axion node, install as many as sixteen SEL-2245-4 modules per system in any combination you want.

# **Front Panel**



Figure 1 SEL-2245-4 AC Metering Module

# **Mechanical Installation**

Each SEL-2242 chassis/backplane has four or ten slots, labeled A-J. Slots B-J support the SEL-2245-4 modules.

To install an SEL-2245-4 module, tip the top of the module away from the chassis, align the notch on the bottom of the module with the slot you want on the chassis, and place the module on the bottom lip of the chassis as *Figure 2* illustrates. The module is aligned properly when it rests entirely on the lip of the chassis.



Figure 2 Proper Module Placement

Next, carefully rotate the module into the chassis, making sure that the alignment tab fits into the corresponding slot at the top of the chassis (refer to *Figure 3*). Finally, press the module firmly into the chassis and tighten the chassis retaining screw.





Figure 3 Final Module Alignment

## **Input Connections**

The SEL-2245-4 CT/PT analog inputs include a dot next to the terminal number to indicate the positive convention. Refer to Specifications for ac analog input ratings and to Figure 4 for terminal assignments. You can configure potential transformer (PT) inputs for 5-400 V and current transformer (CT) inputs for 0-22 A. Configure inputs by adding a Fieldbus I/O connection for each module in ACSELERATOR RTAC® SEL-5033 Software. See the EtherCAT<sup>®</sup> portion in Section 2: Communications in the SEL-5033 Software Instruction Manual for details.




Figure 4 CT/PT Analog Inputs

## **LED** Indicators

The LEDs labeled ENABLED and ALARM are related to EtherCAT network operation. The green ENABLED LED illuminates when the module is operating normally on the network. The ALARM LED illuminates during network initialization or when there is a problem with the network.

## 

Use supply wires suitable for 60°C (140°F) above ambient. See product or manual for ratings.

## 

Utilisez des fils d'alimentation appropriés pour 60°C (140°F) au-dessus ambiante. Voir le produit ou le manuel pour les valeurs nominales.

# **Specifications**

#### Compliance

Designed and manufactured under an ISO 9001 certified quality management system

UL Listed to U.S. and Canadian safety standards (File E220228; NRAQ, NRAQ7)

CE Mark

UKCA Mark

#### **Product Standards**

IEC 60255-26:2013 - Relays and Protection Equipment: EMC IEC 60255-27:2014 - Relays and Protection Equipment: Entre IEC 60255-27:2014 - Relays and Protection Equipment: Safety IEC 60825-2:2004 +A1:2007 +A2:2010 for fiber-optic communications IEC 61850-3:2013 - Comm Systems for Power Utility Automation

#### General

#### **Operating and Storage Temperature Range**

 $-40^{\circ}$  to  $+85^{\circ}$ C ( $-40^{\circ}$  to  $+185^{\circ}$ F) Units should be stored and transported in their original packaging.

Note: Operating temperature evaluated for UL ambient 0° to 40°C.

#### **Operating Environment**

Pollution Degree:	2
Overvoltage Category:	П
Insulation Class:	1
Relative Humidity:	5%-95%, noncondensing
Maximum Altitude:	2000 m
Vibration, Earth Tremors:	Class 1

#### AC Metering Inputs (SEL-2245-4)

	Frequency:	50/60 Hz
	Range:	45–65 Hz
	Typical Accuracy:	±0.005 Hz above 20 V
	Worst-Case Accuracy:	±0.01 Hz above 20 V
	Phase Rotation:	ABC, ACB
	Input Configuration:	3-Wire Delta, 4-Wire Wye
U	pdate Interval	
	Fundamental Metering:	200 Hz
	RMS Metering:	5 Hz
Current Inputs Phase and Neutral		
	I <sub>NOM</sub> :	1 A or 5 A (no settings required)
	Measurement Range:	0.050–22 A Continuous 22–100 A Symmetrical for 25 s
	Thermal Withstand Limit:	500 A for 1 s
	Typical Accuracy:	$\pm 0.1\%$ Fundamental@ $f_{NOM}$ and > 0.6 A $\pm 0.1\%$ RMS@ $f_{NOM}$ and > 0.6 A
	Worst-Case Accuracy:	±2% ± 0.005 A Fundamental ±1% ± 0.005 A RMS
	Angle	
	Range:	±180°
	Typical Accuracy:	$\pm 0.1^\circ$ Fundamental @ $f_{NOM}$ and > 0.6 A
	Worst-Case Accuracy:	$\pm 2^{\circ} @ f_{NOM}$
	Burden:	$< 0.1 \; \mathrm{VA}$ @ $\mathrm{I}_{\mathrm{NOM}}$

## Voltage Inputs

Voltage Inputs	
V <sub>NOM</sub> :	300 V
Measurement Range:	5–400 L-N, 9–693 L-L Vac Fundamental/RMS 5–300 L-N, 9–520 L-L Vac Fundamental/RMS (UL)
Maximum:	600 L-N, 1039 L-L Vac Fundamental/RMS for 10 s
Typical Accuracy:	$\pm 0.1\%$ Fundamental@ $f_{NOM}$ and > 20 V $\pm 0.1\%$ RMS@ $f_{NOM}$
Worst-Case Accuracy:	±2% Fundamental@ f <sub>NOM</sub> ±1% RMS ±0.05 V
Angle	
Range:	±180°
Typical Accuracy:	$\pm 0.1^\circ$ @ $\rm f_{NOM}$ and > 20 V
Worst-Case Accuracy:	$\pm 2^{\circ} @ f_{NOM}$
Burden:	< 0.1 VA
Sequence Components	
Values:	I0, I1, I2, V0, V1, V2
Typical Accuracy	
Magnitude:	$\pm 0.2\%$ @ $f_{\rm NOM}$
Angle:	$\pm 0.2^\circ$ @ $f_{NOM}$ and V > 6.7 V, I > 0.6 A
Worst-Case Accuracy	
Magnitude:	$\pm 3\%$ @ $f_{NOM}$ and V > 6.7 V, I > 0.6 A
Angle:	$\pm 0.2^\circ$ @ $\rm f_{NOM}$ and V > 6.7 V, I > 0.6A
Power and Power Factor (	Per Phase and Three-Phase)
PA, PB, PC, 3P	
Typical Accuracy:	0.1% @ PF > $0.1$
Worst-Case Accuracy:	2%
QA, QB, QC, 3Q	
Typical Accuracy:	0.1% @ PF < $0.9$
Worst-Case Accuracy:	2%
SA, SB, SC, 3S	
Typical Accuracy:	0.1%
Worst-Case Accuracy:	2%
PFA, PFB, PFC, 3PF	
Typical Accuracy:	0.1% @ PF > 0.1
Worst-Case Accuracy:	2%
Synchrophasor	
Conformance:	IEEE C37.118.1-2011 as amended by IEEE C37.118.1a-2014 IEEE C37.118.2-2011
Accuracy:	Level 1 as specified by IEEE C37.118
Measurements:	Software selectable (P or M class)
Voltage:	VA, VB, VC, VS
Current:	IA, IB, IC, IN
Positive-Sequence:	V1, I1
Periodic:	Frequency and df/dt
Processing Rate:	120 Hz

#### Triggered Waveform Recording

Sampling Rates:	1, 2, 4, 8, 24 kHz software selectable
Record Duration:	0.1 second increments from 0.5 s to specified maximum for each sample rate.
Maximum Record Duration:	6 s at 24 kHz 18 s at 8 kHz 36 s at 4 kHz 72 s at 2 kHz 144 s at 1 kHz
Record Pretrigger:	0.05 s minimum to a maximum of (record length -0.05) s
Waveform File Format:	COMTRADE (IEEE C37.111-1999 compliant)
<b>-</b> 1	

## **Type Tests**

#### **Environmental Tests**

Enclosure Protection:	IEC 60529:2001 + CRGD:2003 IP3X excluding the terminal blocks
Vibration Resistance:	IEC 60255-21-1:1988 Vibration Endurance, Severity: Class 2 Vibration Response, Severity: Class 2
Shock Resistance:	IEC 60255-21-2:1988 Bump Withstand, Severity: Class 1 Shock Withstand, Severity: Class 1 Shock Response, Severity: Class 2
Seismic:	IEC 60255-21-3:1993 Quake Response, Severity: Class 2
Cold, Operational and Cold, Storage:	IEC 60068-2-1:2007 -40°C, 16 hours
Dry Heat, Operational and Dry Heat, Storage:	IEC 60068-2-2:2007 +85°C, 16 hours
Damp Heat, Cyclic:	IEC 60068-2-30:2005 25° to 55°C, 6 cycles, 95% relative humidity
Damp Heat, Steady State:	IEC 60068-2-78:2012 93% RH and 55°C for 10 days
Change of Temperature:	IEC 60068-2-14:2009 1 deg. per minute, -40° and +85°C, 5 cycles

#### **Dielectric Strength and Impulse Tests**

Impulse:	IIEC 60255-5:2000 IEEE C37.90-2005
	Severity Level:
	0.5 Joule, 5 kV CT/PT inputs
Dielectric (HiPot):	IEC 60255-5:2000
	IEEE C37.90-2005
	Severity Level:
	2500 Vac CT/PT inputs for 1 minute

#### **RFI and Interference Tests**

Fast Transient, Burst

Immunity:

Magnetic Field

Surge Withstand

Oscillatory Waves

Immunity:

Common Mode Disturbance Immunity:

Emissions

Emissions:

Capability Immunity:

Immunity:

EMC Immunity Slow Damped Oscillatory IEC 61000-4-18:2006 + A1:2010 Severity Level: 2.5 kV common mode Waves: 1 kV differential mode Electrostatic Discharge IEEE C37.90.3-2001 IEC 60255-22-2:2008 Immunity: IEC 61000-4-2:2008 Severity Level: 8 kV contact discharge 15 kV air discharge Radiated RF Immunity: IEEE C37.90.2-2004 Severity Level: 35 V/m IEC 61000-4-3:2008 IEC 60255-22-3:2007 Severity Level: 10 V/m ENV 50204:1995 Digital Radio Telephone RF Immunity: Severity Level: 10 V/m at 900 MHz and 1.89 GHz Conducted RF Immunity: IEC 60255-22-6:2001 IEC 61000-4-6:2008 Severity Level: 10 Vrms IEC 60255-22-5:2008 Surge Immunity: IEC 61000-4-5:2005 Severity Level: 1 kV Line to Line,

2 kV Line to Earth (202 ms filter on RMS voltages and frequencies, 33 ms filter on fundamental frequencies) IEC 60255-22-4:2008

IEC 61000-4-4:2011 Severity Level: Class A: 4 kV, 5 kHz; 2 kV, 5 kHz on communications ports

IEC 61000-4-8:2009 Severity Level: 1000 A/m for 3 seconds, 100 A/m for 1 minute IEC 61000-4-9:2001 Severity Level: 1000 A/m IEC 61000-4-10:2001 Severity Level: 100 A/m

IEEE C37.90.1-2002 Severity Level: 2.5 kV Oscillatory 4.0 kV Fast Transient

IEC 61000-4-12:2006 Severity Level: Ring Wave: 2 kV common, 1.0 kV differential Oscillatory: 2.5 kV common, 1.0 kV differential

IEC 61000-4-16:2002 Frequency: 0 Hz to 150 Hz Severity Level: Level 4, Segment 4: 30 Vrms open-circuit, 15 kHz-150 kHz

Radiated and Conducted IEC 60255-25:2000 Severity Level: Class A Canada ICES-001 (A) / NMB-001 (A)

© 2013–2022 by Schweitzer Engineering Laboratories, Inc. All rights reserved.

All brand or product names appearing in this document are the trademark or registered trademark of their respective holders. No SEL trademarks may be used without written permission. SEL products appearing in this document may be covered by U.S. and Foreign patents.

Schweitzer Engineering Laboratories. Inc. reserves all rights and benefits afforded under federal and international copyright and patent laws in its products, including without limitation software, firmware, and documentation.

The information in this document is provided for informational use only and is subject to change without notice. Schweitzer Engineering Laboratories, Inc. has approved only the English language document.

This product is covered by the standard SEL 10-year warranty. For warranty details, visit selinc.com or contact your customer service representative.

#### SCHWEITZER ENGINEERING LABORATORIES, INC.

2350 NE Hopkins Court • Pullman, WA 99163-5603 U.S.A. Tel: +1.509.332.1890 • Fax: +1.509.332.7990 selinc.com · info@selinc.com





